


Enabler 4P



BJ-240

Control blinds, screens, curtains or other motorized elements

Enabler 4P Motor is a device with 4 pairs of switched relay contacts that allows you to **control two different functions (normally raise and lower) of 4 motorized elements**, such as blinds, curtains, screens, kitchen furniture, etc. The up & down and open & close functions of these elements can be **activated using [our remote controls](#)** or by means of a **switch**.

This device requires [Enabler Core](#) to work.

This device is part of our [environmental control](#) solution.

- Supply voltage: 5VDC
- Power supply: 230VAC
- Controllable with our remotes.
- Size: 109 x 59 x 36 mm.
- Radio Frequency: 433 MHz.
- 4x2 switch inputs for direct manual control.
- Three operating modes selected with a jumper: latched (auto-off at 55 seconds), dead man and combined.
- In the combined mode, the operation depends on the length of the click:

- Short click: latched (auto-off at 55 seconds).

- Long click: dead man.

- Compatible only with 230VAC single phase engines.
- Direct connection to the engine without additional wiring.
- Maximum load: 1000W (5.5 A / cos = 0.8).
- RS-232 port to connect to Enabler Core

